

CARDHOLDER GROUP

1. Creating a cardholder group is a way to segment cardholders into different classes for organizational purposes. Use the search icon and arrows to add specific cardholders to a group.

The screenshot displays the Linear eMERGE interface. On the left, the 'Threat Level Status' is 'SEVERE' and the 'E3 Time' is '10-11-2013 11:23:00'. The main area shows the 'Basic' configuration for a cardholder group. The 'Group Table Name' is 'Residents'. Below this, the 'Card Holder List' section shows a search for 'Suzan Linear' with results: Suzan Linear, Paul Jones, and Sam Smith. The 'Add' button is highlighted with a red box, and a red arrow points from the text in the first step to this button.

| No | Table Name | Card Holder List |
|-----|------------------|------------------|
| New | Group Table Name | Search List All |

DOOR GROUP

1. You can create and add a door group to a specific access level, instead of adding individual doors. Use the search icon and arrows to create a door group.

Configuration > Group Table > Door Group

Basic

Group Table Name * : All Doors

Door List

Door 4
Door 3
Door 2
Door 1

Door 4
Door 3
Door 2
Door 1

Save Reset Cancel

| No | Table Name | Door List |
|----|------------|--------------------------------|
| 1 | All Doors | Door 1, Door 2, Door 3, Door 4 |

New Group Table Name Search List All

[1]

ACCESS LEVEL GROUP

1. You can create an Access Level Group and apply to individual cardholders. Use the search icon and arrows to create the access level group.

Configuration > Group Table > Access Level Group

Basic

Group Table Name * : Employee Access

Access Level List : All Doors, Second Shift

Save Reset Cancel

| No | Table Name | Access Level List |
|----|-----------------|-------------------------|
| 1 | Employee Access | All Doors, Second Shift |

New Group Table Name Search List All

[1]

EXPANSION NODE REPLACEMENT

1. If you need to replace an Expansion Node, go to Client Replacement, select "Edit" and insert the new MAC address and "Save."

Linear®
Building On Innovation.

Threat Level Status
SEVERE

E3 Time
10-11-2013 11:52:05

Configuration > Client Replacement

Basic

Name : Client 1

Type : Door 4

IP Address : 10.5.142.41

MAC Address * : F0:D1:4F:00:08:30

Save Reset Cancel

| No | Name | Type | IP Address | MAC Address |
|----|----------|--------|-------------|-------------------|
| 2 | Client 1 | Door 4 | 10.5.142.41 | F0:D1:4F:00:08:30 |

Name [v] Search List All

[1]

SITE MANAGEMENT

1. In Site Management you can change the site name and logo.
Note: Max 150KB.

Configuration > Site Management

Basic

Site Name : eMerge Site

Site Logo : eMerge.png (Max 150KB - jpg, bmp, png)

| No | Site Name | Site Logo |
|----|--------------|----------------|
| 1 | default site | LogoLinear.jpg |

Site Name

[1]

SITE MANAGEMENT

1. In Site Management you can change the site name and logo.
Note: Max 150KB.
2. The logo has been changed.

Dashboard > Dashboard

Floor * : Default Floor

Door 1 Door 2 Door 3 Door 4

AI 1 AI 2 AI 3 AI 4

AO 1 AO 2 AO 3 AO 4

Please add floor images.

Log ACK Door 1 M-Unlock E-Unlock Lock AO 1 Trigger Stop

| Time | Local Time | Device Name | User Name | Event Description |
|---------------------|---------------------|--------------|-----------|-------------------|
| 10-11-2013 11:57:42 | 10-11-2013 11:57:42 | 10.5.142.214 | admin | Site Data Update |
| 10-11-2013 11:56:09 | 10-11-2013 11:56:09 | 10.5.142.214 | admin | Site Data Update |
| 10-11-2013 11:55:51 | 10-11-2013 11:55:51 | 10.5.142.214 | admin | Site Data Update |
| 10-11-2013 11:55:21 | 10-11-2013 11:55:21 | 10.5.142.214 | admin | Site Data Update |